

An Ultra-Compact VHF CRLH-Line Bandpass Filter Less Than $(\lambda_g/19)^2$ With a Broad Stopband

M. K. Khattak¹, S. Kahng¹, J. Ju²

Incheon National University, Dept. Of Info. & Telecomm. Eng., Songdo, 406-772, Incheon, Korea
 MiEMI-sol. Lab., Yonsu, Incheon, 406-772, Incheon, Korea
 s-kahng@incheon.ac.kr

Abstract- A VHF bandpass filter is designed to be extremely compact and working suitable for a lighter and high-fidelity T-DMB receiver. A super-small distributed element CRLH unit cell is devised based on the T-type equivalent circuit and the three blocks of the unit cell are cascaded by matching the neighboring impedances. Therefore, the overall footprint of the filter is less than $(\text{wavelength}/19) \times (\text{wavelength}/34)$, and the passband with low insertion- and return loss is obtained as demanded in the 180-MHz T-DMB service. Besides, this zeroth-order resonance filter shows an excellent performance of suppressing the spurious harmonics over a very broad stopband up to several GHz.

I. INTRODUCTION

Since C. Caloz and T. Itoh introduced the concept of the composite right- and left-handed (CRLH) transmission-line(TL) and its lumped-element versions, it has been applied to improve RF hardware performances or reduce their physical sizes[1]. Negative resonance as well zeroth-order resonance is instrumental in size-reduction of microwave components and antennas [2]. Backward-waves can be used to increase the beam-scanning range of a leaky-wave antenna [3]. F. Martin et al formed pairs of slot rings coupled to capacitive gaps on the top surface of the microstrip filters [4]. While most of microwave CRLH-type passive components aim to work in the frequency above 1 GHz, a number of literatures present the RF component designs performing well in the UHF-band or even the VHF-region where it is usually challenging to reduce the physical sizes effectively and create the left-handed waves using the distributed CRLH elements [5-8].


In this paper, an enhanced compact VHF bandpass filter is designed. A spiral short-circuited stub is adopted for the CRLH unit-cell to increase the quality-factor of the shunt inductor and avoid the self-resonance caused harmonics, instead of the straight line. Along with this, an increased number of fingers with shorter lengths make the interdigital coupled-lines to minimize the inductive parasitics. These approaches will turn out appropriate to have better return loss result and harmonic-rejection over a broader stopband(above the 11th harmonic) compared to [6]. Notably, the overall area of the proposed filter is measured to be smaller than

$(\text{wavelength}/19) \times (\text{wavelength}/34)$. In the passband of 180 MHz, the insertion loss is even lower than 2 dB with return loss of $|S_{11}| \leq -15$ dB.

II. INITIAL AND ADVANCED DESIGNS FOR THE PROPOSED FILTER

In the beginning, we design the unit cell to resonate at 180 MHz primarily, which will be unfolded to form the pass-band by coupling the adjacent cells in a later section. This physical resonator is first modelled by the equivalent circuit of the CRLH TL which is found in other literatures [1-8].

As was done in the aforementioned references, the series- and shunt LC pairs exist together in the equivalent circuit model, and this basic circuit is possibly expressed as a T-type as in Fig. 1a and a microstrip line structure corresponding to this symmetric equivalent circuit expression of the CRLH-TL unit cell is suggested as in Fig. 1b. Compared to other works, a clear difference can be addressed with a view to circumventing a couple of the previous shortcomings. A spiral short-circuited stub is adopted for the CRLH unit-cell to increase the quality-factor of the shunt inductor to have a steeper skirt at the edges of the passband and avoid the self-resonance causing harmonics, instead of the long straight line. Besides, with this, an increased number of fingers with shorter lengths make the interdigital coupled-lines to minimize the inductive parasitics.



(a)




Figure.1. Equivalent circuit, geometry of the CRLH-TL unit-cell, and representative characteristic ($l_s = 4.7$, $l_c = 10.36$, $w_s = 4.7$, $w_c = 9.16$, unit: mm) (a) Equivalent circuit (b) Physical shape of the CRLH-TL unit cell (c) Bloch impedance.

Using the equations as in [5-7], the circuit elements are calculated for operating in T-DMB (174–216MHz) as 16.33 nH, 0 nH, 8.76 pF, 30.37 pF as L_L , L_R , C_L , C_R , respectively with Bloch impedance Z_B of 59 Ω . Fig. 1(c) implies the center frequency the passband is successfully achieved at 180 MHz with impedance matching as Z_B . This unit cell is replicated to its multiple cells and they are cascaded to form a bandpass filter.





Figure. 2. Geometry of the proposed VHF bandpass filter and its frequency response (a) Physical shape (b) S_{11} and S_{21} .

As the advanced step, the 3-cell structure is implemented and fabricated. The overall footprint of the filter is $(\lambda_g/19) \times (\lambda_g/34)$, where λ_g is the guided wavelength, which presents effective size-reduction. Seeing S_{11} and S_{21} , the passband is created in the VHF-band with a slight shift due to cheap fabrication. Low insertion-loss is obtained as below 2 dB. Furthermore, the spurious suppression is expanded up to several GHz with $|S_{21}| < -30$ dB.

III. CONCLUSION

A super-compact VHF-band filter was designed based on the modified CRLH unit-cells. Its passband, insertion- and return loss are acceptable. Also, a very broad stopband is noteworthy.

IV. ACKNOWLEDGEMENT

This work was supported by ICT R&D program of MSIP/IITP[2014-044-047-001, Dev. of radio services Antenna for the future Using Hybrid propagation medium].

REFERENCES

- [1] C. Caloz, and T.Itoh, *Electromagnetic metamaterials: transmission line : theory and microwave application*, John Wiley & Sons, USA, 2006.
- [2] K. Kanhg, S. Kahng, I. Yang and Q. Wu, "A Bandwidth-Enlarged and Isolation-Enhanced ZOR MIMO Antenna, Shorter than $0.11\lambda_g$," *Microwave Journal*, Vol.57, No.9, pp. 128-136, September 2014.
- [3] H.V. Nguyen, S. Abielmona, A. Rennings and C. Caloz, "Pencil-Beam Full-Space Scanning 2D CRLH Leaky-Wave Antenna Array," in *Proc. of ISSSE, 2007*, pp.139 - 142, July 30 2007-Aug. 2 2007.
- [4] R. Marques, F. Martin, M. Sorolla, , *Metamaterials with negtive parameters: theory, design, and microwaves applications*, John Wiley & Sons, USA, 2009
- [5] G. Jang and S. Kahng, "Compact metamaterial zeroth-order resonator bandpass filter for a UHF band and its stopband improvement by transmission zeros," *IET Microwaves, Antennas & Propagation*, Vol. 5, Iss. 10, pp. 1175–1181, 2011.
- [6] U.-C. Shin and S. Kahng, "Miniaturization and Rejection-Enhancement of the Bandpass Filter for the T-DMB Application Using a Metamaterial Structure of the Zero-Order Resonator Coupling," *Journal of Korean Institute of Electromagnetic Engineering and Science*, Vol.19 , No.12, pp.1462-1469, Dec. 2008.
- [7] G. Jang and S. Kahng, "A Novel Compact Metamaterial Zeroth Order Resonant Bandpass Filter for a VHF Band and Its Stopband Improvement by Transmission Zeros", *Journal of Electromagnetic Engineering and Science* ,Vol. 13, No. 4, pp. 263-266 , Dec. 2013.
- [8] B. Ghahremani, M. Kamyab and M. Golmohammadi, "The Design of A Novel Compact CRLH Band-pass FilterR With Harmonics Suppression," *Progress In Electromagnetics Research C*, Vol. 16, pp.99-110, 2010.